

**AN-10BT-10B2 | 10Base-2 (Thinnet Coax BNC) to 10Base-T Ethernet Converter**

- Converter provides easy and affordable solution for connecting your existing Thin Ethernet adapter card or Thinnet Coax BNC Ethernet Network to a 10Base-T UTP network.
- converts signals from Thin Ethernet for transmission over Unshielded Twisted-Pair (UTP) cable to a 10Base-T hub.

**Ports:**

- 1xRJ-45 from (Hub/Switch)
- 1xBNC socket to 10 Base-2

**Power supply:**

- Input 110V or 220V AC
- Output 9V DC, 1 Amp

**Topology**

- Baseband Twisted Pair expand upon to 4 level Thinnet up to 30 Hubs

**Standards**

10 to 90% (non-condensing)  
Meets FCC Class A Subpart B of Part 15  
Requirments  
IEEE 802.3 10Base-T/10Base-2  
Star CSMA/CD

**Cable lenghts:**

- 100 M max. per UTP cables
- 185 M max. per Thin Ethernet

**Environmental:**

- Temperature: 0 to 55C (standard operating)
- Humidity: 10 to 90% (non-condensing)



Dimensions: **0.79" (H) x 2.17" (W) x 4.09" (D)**

**Kullanım Alanları**

- RJ-45 To BNC Media Converter / Çevirici
- 10Base-T Twisted Pair UTP to 10Base-2 BNC Koaksiyel ağ bağdaştırıcı
- Bilgisayar üzerinde bulunan Thinnet BNC koaksiyel ethernet adaptörünün UTP networkte Switch / Hub ağına bağlantısı
- Koaksiyel kablo üzerinden ethernet mesafe uzatma. Maksimum 185 metre

Talepleriniz için bize ulaşın.



[www.gym-tech.net](http://www.gym-tech.net)

| Tel : +90 212 3204030

| Fax : +90212 3200255

| e-mail : [info@telkoink.com](mailto:info@telkoink.com)

| Address : Perpa Ticaret Merkezi, A Blok No.516 Şişli/İstanbul

| **Haberleşme & Telekom & Network Ürünleri**



[www.telkoink.com](http://www.telkoink.com)