

## CLR-SA-BNC-MF

### Video Lightning Protector



#### Overview

CLR-SA-BNC-MF is a coaxial signal surge arrester for coaxial computer systems like 100BASE-2 video and camera systems, etc. It is used to protect the indirect thunder influence or other instantaneous overvoltage surges

#### Features

- Nominal discharge current (8/20us)(In): 10KA
- Operating voltage (Un): DC5V DC12V DC24V
- Frequency band : 20KHz. 1MHz. 40MHz . 100MHz
- Impedance: 50Ω 75Ω
- Voltage protection level (up): 120V
- Interface connector type: BNC Male and Female
- Insertion loss: 0,2db

CLR-SA-BNC-MF series can add remote signal control function

#### Ordering Information

CLR-SA-BNC-MF

Video Lightning Protector