

GENEL

- Fiber Optik ayarlı zayıflatıcı 2.5-60dB aralığında zayıflatma yapabilmelidir.
- Cihaz dijital göstergeli olmalıdır.
- Cihaza USB portu üzerinden bilgisayar ile bağlantı yapılabilmelidir.
- Cihazın bataryası USB portu üzerinden şarj olmalıdır.
- Cihaz en az 20 saat sürekli çalışabilmelidir.
- Girişindeki 1260~1650nm dalgaboyundaki sinyalleri zayıflatabilmelidir.
- Kullanıcılar sık kullandıkları zayıflatma değerlerini cihaza set edip, daha sonra bu değerleri hızlı bir şekilde seçebilmelidir.
- Fiber tipi 9/125µm singlemode olmalıdır.
- Cihazın "insertion loss" değeri 2,5dB'den az olmalıdır.
- Maksimum giriş gücü +21dBm olmalıdır.
- Çıkış gücü aralığı +18 ~ -55 dBm olmalıdır.
- 0.01dB artım adımlarıyla ayrılabilmelidir.
- Zayıflatma kesinlik değeri @+25°C sıcaklıkta ±0.25dB olmalıdır
- "Return Loss" değeri 55dB'den az olmalıdır.
- Güç tasarrufu amacıyla 5 dakika boşta kaldığında otomatik olarak kendini kapatmalıdır.
- Cihazın bataryası Li-ion olmalıdır.

Cihaz resmi

Address : Perpa Ticaret Merkezi, A Blok No.516 Şişli/İstanbul | Tel : +90 212 3204030 | Fax : +90212 3200255 | e-mail : info@telkolink.com

www.telkolink.com

© 2009 telkolink Inc. All rights reserved. Information in this document is subject to change without notice. All company names, logos, and product designs that are trademarks or registered trademarks are the property of their respective owners. 617-000175 Rev. C

Haberleşme sistemlerinde yüksek performansı yakalayın

